



DIY WORKSHOP



HOME ESSENTIAL APPLIANCE BACK-UP



SMALL OUTDOOR EVENTS



MARKET STALLS/ MOBILE BUSINESS



LIGHT AGRICULTURE

## PRODUCT DETAILS

The Welling and Crossley P3750 is an AVR (automatic voltage regulated) generator with E-start. Supplied with transport kit (handles and wheels), this generator is Euro 5 emissions compliant. The generously sized 15L fuel tank and economical motor allows longer run times. The WC-P3750 packs a lot of power in a compact footprint.

## APPLICATIONS

- DIY workshops to power small to medium tools and lights
- Home back-up solution for essential appliances
- Outdoor events for lights, sound systems etc
- Mobile businesses or market stalls for powering small appliances

## FEATURES

- 2 x IP44 Outlets (single phase - 15 Amp)
- USB A and USB C outlets
- Multiple start options: Recoil start, push-button electric start, wireless remote start, 2-wire remote start
- Transport kit included: Fold-out wheelbarrow style handle and large wheels
- Powerful & efficient: Air cooled OHV 4-Stroke engine with large fuel tank
- Digital V/F/T Display (Volts, Frequency, Time)
- Transistorised Ignition
- Low oil alarm, overload alarm, output indicator
- 2 year Welling and Crossley Warranty (battery excluded)



Total harmonic distortion 6 - 8%



EURO 5

## TECHNICAL DATA

MODEL RATING	3.75kVa with AVR
POWER FACTOR	0.8
MAX. AC OUTPUT	3200W
RATED AC OUTPUT	2800W Max 12 Amp
RATED MOTOR SPEED	3000rpm
RATED VOLTAGE	230/240V AC 1 Ph / 50Hz
ENGINE MODEL	WC-230: Euro 5 emissions compliant
ENGINE TYPE	Single cylinder, 4 stroke, OHV air cooled petrol
DISPLACEMENT	223cc

OIL	0.6 litres SAE10W-30
SPARK PLUG	Torch F6TC, Champion RN9YC
NOISE LEVEL @ 7M	68 dBA
FUEL TYPE	Petrol - 91 octane unleaded.
FUEL TANK CAPACITY	15L
FUEL CONSUMPTION	Approx 0.6 L/Hr @ 1/4 load
PACKAGING (L X W X H)	605 x 470 x 507mm
PRODUCT (L X W X H)	600 x 580 x 560mm
DRY WEIGHT	45kg